SWF-86382340-10-H1

Waveguide Highpass Filter, W Band

Description:

Model SWF-86382340-10-H1 is a W band waveguide highpass filter with a passband frequency of 86 GHz and higher and a rejection frequency from DC to 82 GHz. The filter provides a nominal insertion loss of 1.0 dB in its passband and a typical rejection of 40 dB at 82 GHz and below. Because the passband frequency can be set by modifying the design,



other highpass filters with various passband are offered under different model numbers.

Features:

- Low Cost
- Low Insertion Loss
- High Rejection

Applications:

- Communication Systems
- Radar Systems
- Sub-assemblies

Electrical Specifications:

Parameter	Minimum	Typical	Maximum
Passband Frequency	86 GHz		
Passband Insertion Loss		1.0 dB	
Rejection Frequency	DC		82 GHz
Rejection		40 dB	
Power Handling			100 W (CW)
Specification Temperature		+25 °C	
Operating Temperature	-40 °C	Contraction of the	+85 °C

Mechanical Specifications:

Item Specification		
RF Ports	WR-10 with UG-387/U-M Flange	
Material	Aluminum	
Finish	Gold Plated	
Weight	0.4 Oz	
Size	1.20" (L) X 0.75" (Ø)	
Outline	WF-HW	



www.sagemillimeter.com | 3043 Kashiwa Street, Torrance, CA 90505 Phone: 424-757-0168 | Fax: 424-757-0188 | Email: sales@sagemillimeter.com Rev. 1.0

SWF-86382340-10-H1

Waveguide Highpass Filter, W Band



Mechanical Outline: (Unless otherwise specified, all dimensions are in inches [millimeters])

Note:

• SAGE Millimeter, Inc. reserves the right to change the information presented without notice.

Caution:

• Any foreign objects in the waveguide will cause performance degradation and possible device damage.





www.sagemillimeter.com | 3043 Kashiwa Street, Torrance, CA 90505 Phone: 424-757-0168 | Fax: 424-757-0188 | Email: sales@sagemillimeter.com Rev. 1.0