DRV2511-Q1 适用于螺线管和音圈的 8A 汽车类触觉驱动器

1 特性

- 宽工作电压范围 (4.5V - 26V)
- 能够处理 30V 电压
- 大电流驱动（峰值电流达 8A）
- 低 $R_{DS(on)}$，完整 H 桥输出
- 集成故障保护
  - 短路保护
  - 过热保护
  - 过压和欠压保护
  - 故障报告
- 模拟输入
- 专用中断引脚
- 具有符合 AEC-Q100 标准的下列结果：
  - 器件温度 1 级：-40°C 至 125°C 的环境运行温度范围
  - 器件人体放电模式 (HBM) 静电放电 (ESD) 分类等级 H2
  - 器件组件充电模式 (CDM) ESD 分类等级 C4B

2 应用

- 电磁致动器驱动器
  - 音圈
  - 螺线管
- 机械按钮替代产品
- 汽车类触觉 应用
  - 信息娱乐
  - 中央控制台
  - 方向盘
  - 车门板
  - 座椅

3 说明

DRV2511-Q1 器件是一款专为感性负载（例如，螺线管和音圈）而设计的大电流触觉驱动器。

输出级含一个完整 H 桥，能够提供 8A 峰值电流。

DRV2511-Q1 器件提供欠压闭锁、过流保护和过热保护等多种保护功能。


DRV2511-Q1 器件符合汽车类产品标准。

器件信息(1)

器件型号	封装	封装尺寸（标称值）
DRV2511-Q1	HTSSOP (32)	11 mm x 6.20 mm

(1) 要了解所有可用封装，请见数据表末尾的可订购产品附录。

简化电路原理图



An IMPORTANT NOTICE at the end of this data sheet addresses availability, warranty, changes, use in safety-critical applications, intellectual property matters and other important disclaimers. PRODUCTION DATA.

目录

1 特性 1
2 应用 1
3 说明 1
4 修订历史记录 2
5 **Pin Configuration and Functions** 3
6 **Specifications** 4
6.1 Absolute Maximum Ratings 4
6.2 ESD Ratings 4
6.3 Recommended Operating Conditions 4
6.4 Thermal Information 4
6.5 Electrical Characteristics 6
6.6 Switching Characteristics 6
6.7 Typical Characteristics 7
7 **Detailed Description** 8
7.1 Overview 8
7.2 Functional Block Diagram 8
7.3 Feature Description 9
7.4 Device Functional Modes 11
7.5 Programming 11
8 **Application and Implementation** 12
8.1 Application Information 12
8.2 Typical Applications 12
9 **Power Supply Recommendations** 16
10 **Layout** 16
10.1 Layout Guidelines 16
10.2 Layout Example 16
11 器件和文档支持 17
11.1 器件支持 17
11.2 商标 17
11.3 静电放电警告 17
11.4 Glossary 17
12 机械、封装和可订购信息 18

4 修订历史记录


注：之前版本的页码可能与当前版本有所不同。

Changes from Original (June 2016) to Revision A	**Page**
• 发布为量产数据。	1

Copyright © 2016, Texas Instruments Incorporated

5 Pin Configuration and Functions

DAP Package
32-Pin HTSSOP
Top View



Pin Functions

PIN		TYPE	DESCRIPTION
NAME	NO.		
GND	1, 9, 10, 11, 22, 25, 28	P	Ground.
EN	2	I	Device enable pin.
INTZ	3	O	General fault reporting. Open drain. INTZ = High, normal operation INTZ = Low, fault condition
IN+	4	I	Positive differential input.
IN-	5	I	Negative differential input.
REG	6, 7	P	Internally generated gate voltage supply. Not to be used as a supply or connected to any component other than a 1 µF X7R ceramic decoupling capacitor and the MODE resistor divider.
GAIN	8	I	Selects Gain.
STDBY	12	I	Standby pin.
FS2	13	I	Output switching frequency selection.
FS1	14	I	Output switching frequency selection.
FS0	15	I	Output switching frequency selection.
N/C	16	N/C	Pin should be left floating.
AVDD	17	P	Analog Supply, can be connected to VBAT for single power supply operation.
PVDD	18, 19, 31, 32	P	Power supply.
BSTN	20, 24	P	Boot strap for negative output, connect to 220 nF X5R, or better ceramic cap to OUT-.
OUT-	21, 23	O	Negative output.
BSTP	26, 30	P	Boot strap for positive output, connect to 220 nF X5R, or better ceramic cap to OUT+.

Copyright © 2016, Texas Instruments Incorporated

Pin Functions (continued)

PIN		TYPE	DESCRIPTION
NAME	NO.		
OUT+	27, 29	O	Positive output.
Thermal Pad or PowerPAD™		G	Connect to GND for best system performance. If not connected to GND, leave floating.

6 Specifications

6.1 Absolute Maximum Ratings

over operating free-air temperature range (unless otherwise noted) (1)

		MIN	MAX	UNIT
Supply voltage	PVDD, AVDD	–0.3	30	V
Input voltage, V_I	IN+, IN-	–0.3	6.3	V
	GAIN	–0.3	VREG + 0.3	
	EN	–0.3	PVDD + 0.3	
Current	DC current on PVDD, GND, OUT+, OUT-	–8	8	A
Operating free-air temperature, T_A		–40	125	°C
Storage temperature range, T_{stg}		–50	150	

(1) Stresses beyond those listed under *Absolute Maximum Ratings* may cause permanent damage to the device. These are stress ratings only, which do not imply functional operation of the device at these or any other conditions beyond those indicated under *Recommended Operating Conditions*. Exposure to absolute-maximum-rated conditions for extended periods may affect device reliability.

6.2 ESD Ratings

			MIN	MAX	UNIT
$V_{(ESD)}$	Electrostatic discharge	Human body model (HBM), per ANSI/ESDA/JEDEC JS-001, all pins (1)	–2000	2000	V
		Charged device model (CDM), per JEDEC specification JESD22-C101, all pins (2)	–450	450	

(1) JEDEC document JEP155 states that 500-V HBM allows safe manufacturing with a standard ESD control process.
(2) JEDEC document JEP157 states that 250-V CDM allows safe manufacturing with a standard ESD control process.

6.3 Recommended Operating Conditions

over operating free-air temperature range (unless otherwise noted)

		MIN	NOM	MAX	UNIT
VDD	Supply voltage. PVDD, AVDD.	4.5		26	V
V_{IH}	High-level input voltage. STDBY, EN, FS0, FS1, FS2.	2			V
V_{IL}	Low-level input voltage. STDBY, EN, FS0, FS1, FS2.			0.8	V
V_{OL}	Low-level output voltage. INTZ, $R_{PULL-UP}$ = 100 kΩ, PVDD = 26 V.			0.8	V
I_{IH}	High-level input current. STDBY, EN, FS0, FS1, FS2. (V_I = 2 V, PVDD = 26 V).			50	µA
R_L	Minimum load Impedance.		1.65		Ω
L_o	Output-filter Inductance.	1			µH

6.4 Thermal Information

THERMAL METRIC (1)		DRV2511-Q1 DAP 32 PINS	UNIT
$R_{\theta JA}$	Junction-to-ambient thermal resistance	32.4	°C/W
$R_{\theta JC(top)}$	Junction-to-case (top) thermal resistance	17.2	°C/W

(1) For more information about traditional and new thermal metrics, see the *Semiconductor and IC Package Thermal Metrics* application report, SPRA953.

Copyright © 2016, Texas Instruments Incorporated

Thermal Information (continued)

THERMAL METRIC(1)		DRV2511-Q1 DAP 32 PINS	UNIT
$R_{\theta JB}$	Junction-to-board thermal resistance	17.3	°C/W
ψ_{JT}	Junction-to-top characterization parameter	0.4	°C/W
ψ_{JB}	Junction-to-board characterization parameter	17.2	°C/W
$R_{\theta JC(bot)}$	Junction-to-case (bottom) thermal resistance	1	°C/W

Copyright © 2016, Texas Instruments Incorporated

6.5 Electrical Characteristics

T_A = 25°C, AVCC = PVDD = 12 V, R_L = 5 Ω (unless otherwise noted)

PARAMETER		TEST CONDITIONS	MIN	TYP	MAX	UNIT
$\lvert V_{OS} \rvert$	Output offset voltage (measured differentially)	V_I = 0 V, Gain = 36 dB		1.5	15	mV
I_{VDD}	Quiescent supply current	No load or filter		20		mA
$I_{VDD(SD)}$	Quiescent supply current in shutdown mode	No load or filter		35		µA
$I_{VDD(STDBY)}$	Quiescent supply current in standby mode	No load or filter		11		mA
$r_{DS(on)}$	Drain-source on-state resistance, measured pin to pin	T_J = 25°C		60		mΩ
G	Gain	R1 = open, R2 = 20 kΩ	19	20	21	dB
		R1 = 100 kΩ, R2 = 20 kΩ	25	26	27	
		R1 = 100 kΩ, R2 = 39 kΩ	31	32	33	dB
		R1 = 75 kΩ, R2 = 47 kΩ	35	36	37	
V_{REG}	Regulator voltage		6.4	6.9	7.4	V
BW	Full Power Bandwidth			60		kHz
V_O	Output voltage (measured differentially)	Measured at PVDD = 26V		50		V
PSRR	Power supply ripple rejection	200 mVpp ripple at 1 kHz, Gain = 20 dB		–70		dB
CMRR	Common-mode rejection ratio			–56		dB
f_{OSC}	Oscillator frequency (with PWM duty cycle < 96%)	FS2 = 0, FS1 = 0, FS0 = 0	376	400	424	kHz
		FS2 = 0, FS1 = 0, FS0 = 1	470	500	530	
		FS2 = 0, FS1 = 1, FS0 = 0	564	600	636	
		FS2 = 0, FS1 = 1, FS0 = 1	940	1000	1060	
		FS2 = 1, FS1 = 0, FS0 = 0	1128	1200	1278	
	Power-on threshold			4.1		V
	Power-off threshold			28		V
	Thermal trip point			150		°C
	Thermal hysteresis			15		°C
	Over-current trip point			13		A
	Over-voltage trip point			28		V

6.6 Switching Characteristics

over operating free-air temperature range (unless otherwise noted)

PARAMETER		TEST CONDITIONS	MIN	TYP	MAX	UNIT
t_{on-sd}	Turn-on time from shutdown to waveform	EN = Low to High, STBY = Low		10		ms
t_{OFF-sd}	Turn-off time	EN = High to Low		5		µs
$t_{on-stdby}$	Turn-on time from standby to waveform	EN = High, STBY = High to Low		6		µs

版权 © 2016, Texas Instruments Incorporated

6.7 Typical Characteristics




图 1. Shutdown Current vs VDD Voltage




图 2. Standby Current vs VDD Voltage

7 Detailed Description

7.1 Overview


The DRV2511-Q1 device is a high current haptic driver specifically designed for inductive loads, such as solenoids and voice coils.

The output stage consists of a full H-bridge capable of delivering 8 A of peak current.

The design uses an ultra-efficient switching output technology developed by Texas Instruments, but with features added for the automotive industry. The DRV2511-Q1 device provides protection functions such as undervoltage lockout, over-current protection and over-temperature protection. This technology allows for reduced power consumption, reduced heat, and reduced peak currents in the electrical system.

The DRV2511-Q1 device is automotive qualified.

7.2 Functional Block Diagram



版权 © 2016, Texas Instruments Incorporated

7.3 Feature Description

7.3.1 Analog Input and Configurable Pre-amplifier

The DRV2511-Q1 device features a differential input stage that cancels common-mode noise that appears on the inputs. The DRV2511-Q1 device also features four gain settings that are configurable via external resistors.

表 1. Gain Configuration Table

GAIN	R1	R2	INPUT IMPEDANCE
20 dB	5.6 kΩ	open	60 kΩ
26 dB	20 kΩ	100 kΩ	30 kΩ
32 dB	39 kΩ	100 kΩ	15 kΩ
36 dB	47 kΩ	75 kΩ	9 kΩ




图 3. Gain Configuration

7.3.2 Pulse-Width Modulator (PWM)

The DRV2511-Q1 device features BD modulation scheme with high bandwidth, low noise, low distortion, and excellent stability.

The BD modulation scheme allows for smaller ripple currents through the load. Each output switches from 0 V to the supply voltage. With no input, the OUT+ and OUT- pins are in phase with each other so that there is little or no current in the load. For positive differential inputs, the duty cycle of OUT+ is greater than 50% and the duty cycle of OUT- is lower than 50% for a positive differential output voltage. The opposite is true for negative differential inputs. The voltage accross the load sits at 0 V throughout most of the switching period, reducing the switching current, which reduces the I^2R losses in the load.

版权 © 2016, Texas Instruments Incorporated




图 4. BD Mode Modulation

7.3.3 Designed for low EMI

The DRV2511-Q1 device design has minimal parasitic inductances due to the short leads on the package. This dramatically reduces EMI that results from current passing from the die to the system PCB. The design incorporates circuitry that optimizes output transitions that causes EMI. Follow the recommended design requirements in the *Design Requirements* section.

7.3.4 Device Protection Systems

The DRV2511-Q1 device features a complete set of protection circuits carefully designed to protect the device against permanent failures due to shorts, over-temperature, over-voltage, and under-voltage scenarios. The INTZ pin signals if an error is detected.

版权 © 2016, Texas Instruments Incorporated

表 2. Fault Reporting Table

FAULT	TRIGGERING CONDITION	INTZ	ACTION	LATCH?
Over-current	Output short or short to PVDD or GND	pulled low	output in high impedance	Latched
Over-temperature	T_j > 150 ºC	pulled low	output in high impedance	Latched
Under-voltage	PVDD < 4.5 V	-	output in high impedance	Self-clearing
Over-voltage	PVDD > 27 V	-	output in high impedance	Self-clearing

When the "Latched" conditions happen, the device must be reset with the EN signal in order to clear the fault. If automatic recovery from these conditions is desired, connect the INTZ pin directly to the EN pin. This allows the INTZ pin function to automatically drive the EN pin low which clears the latched condition.

7.4 Device Functional Modes

The DRV2511-Q1 device has multiple power states to optimize power consumption.

7.4.1 Operation in Shutdown Mode

The NRST pin of the DRV2511-Q1 device puts the device in a shutdown mode. When NRST is asserted (logic low), all internal blocks of the device are off to achieve ultra low power.

7.4.2 Operation in Standby Mode

The STDBY pin of the DRV2511-Q1 device puts the device in a standby mode. When STDBY is asserted (logic high), some internal blocks of the device are off to achieve low power while preserving the ability to wake up quickly to achieve low latency waveform playback.

7.4.3 Operation in Active Mode

The DRV2511-Q1 device is in active mode when it has a valid supply, and it is not in either shutdown or standby modes. In this mode the DRV2511-Q1 device is fully on and reproducing at the output the input times the gain.

7.5 Programming

7.5.1 Gain

The DRV2511-Q1 device has a configurable gain that is controlled through external resistors. Please see the Analog Input and Configurable Pre-amplifier section for more details.

版权 © 2016, Texas Instruments Incorporated

8 Application and Implementation

注

Information in the following applications sections is not part of the TI component specification, and TI does not warrant its accuracy or completeness. TI's customers are responsible for determining suitability of components for their purposes. Customers should validate and test their design implementation to confirm system functionality.

8.1 Application Information

The DRV2511-Q1 device is a high-efficiency driver for inductive loads, such as solenoids and voice-coils. The typical use of the device is on haptic applications where short, strong waveforms are desired to create a haptic event that will be coming from the application processor.

8.2 Typical Applications

8.2.1 Single-Ended Source

To use the DRV2511-Q1 with a single-ended source, apply either a voltage divider to bias INB to 3 V, tie to GND or use a 0.1-μF cap from INB to GND to have the device self bias. Apply the single-ended signal to the INA pin.




图 5. Typical Application Schematic

8.2.1.1 Design Requirements

For most applications the following component values found in 表 3 below can be used.

版权 © 2016, Texas Instruments Incorporated

Typical Applications (接下页)

表 3. Component Requirements Table

COMPONENT	DESCRIPTION	SPECIFICATION	TYPICAL VALUE
C1	Supply capacitor	Capacitance	22 µF and 0.1 µF for PVDD & AVDD
C2/C3	Boost capacitor	Capacitance	0.22 µF
C4/C5	Output snubber capacitor	Capacitance	470 pF
C6	Regulator capacitor	Capacitance	1 µF
C9	Input decoupling capacitor	Capacitance	0.1 µF
R1/R2	Output snubber resistor	Resistance	3.3 Ω
$R_{(PU)}$	Pull-up resistor	Resistance	100 kΩ

8.2.1.2 Detailed Design Procedure

8.2.1.2.1 Optional Components

Note that in the diagrams, there are a few optional external components. These optional external components may be needed in the application to meet EMI/EMC standards and specifications by filters necessary frequency spectrums.

8.2.1.2.2 Capacitor Selection

A bulk bypass capacitor should be mounted between VBAT and GND. The capacitance needs to be >22 uF with a X5R or better rating on the power pins to GND. Also include two ceramic capacitors in the ranges of 220 pF to 1 uF and 100 nF to 1 uF. The bootstrap capacitors, BSTA and BSTB, should be 220-nF ceramic capacitors of quality X5R or better rated for at least the maximum rating of the pin.

8.2.1.2.3 Solenoid Selection

The DRV2511-Q1 solenoid driver can accommodate a variety of solenoids. Solenoids should have an equivalent resistance of 1.6 Ω or greater. Solenoids with lower resistances are prone to driving high currents. A maximum peak current of 8-A should not be exceeded. The DRV2511-Q1 will go into a shutdown mode to protect itself from overcurrent.

8.2.1.2.4 Output Filter Considerations

The output filter is optional and is mainly for limiting peak currents. A second-order Butterworth low-pass filter with the cut-off frequency set to a few kilohertz should be sufficient. See 公式 2, 公式 3, and 公式 4 for example filter design.

$$H(s) = \frac{1}{s^2 + \sqrt{2}s + 1} \quad (1)$$

$$L_x = \frac{\sqrt{2} \times R_L}{2\omega_o} \quad (2)$$

$$2 \times C_F = \frac{\sqrt{2}}{2 \times \frac{R_L}{2} \times \omega_0} \quad (3)$$

$$\omega_0 = 2\pi \times f \quad (4)$$

8.2.1.3 Application Curves

These application curves were taken using an HA200 solenoid with a 100-g mass, and the acceleration was measured using the DRV-AAC16-EVM accelerometer. The following scales apply to the graphs:

- Output Differential Voltage scale is shown on the plots at 5-V/div
- Acceleration scale is 5.85-G/div
- Current scale is 2-A/div

版权 © 2016, Texas Instruments Incorporated




图 6. Voltage and Acceleration vs Time (Input Square Wave)




图 7. Voltage and Acceleration vs Time (Square Wave)




图 8. Voltage and Acceleration vs Time (Ramp Wave)




图 9. Voltage and Acceleration vs Time (1/2 Sine Wave)

8.2.1.4 Differential Input Diagram

To use the DRV2511-Q1 with a differential input source, apply both inputs differentially from a control source (GPIO, DAC, etc...).

版权 © 2016, Texas Instruments Incorporated




图 10. Typical Application Schematic

9 Power Supply Recommendations

The DRV2511-Q1 device operates from 4.5 V - 26 V and this supply should be able to handle high surge currents in order to meet the high currrent draws for haptics effects. Additionally the DRV2511-Q1 should have 22-µF and 0.1-µF ceramic capacitors near the PVDD & AVDD pins for additional decoupling from trace routing.

10 Layout

10.1 Layout Guidelines

The EVM layout optimizes for thermal dissipation and EMC performance. The DRV2511-Q1 device has a thermal pad down, and good thermal conduction and dissipation require adequate copper area. Layout also affects EMC performance. It is best practice to use the same/similiar layout as shown below in the DRV2511Q1EVM.

10.2 Layout Example




图 11. DRV2511-Q1 EVM

版权 © 2016, Texas Instruments Incorporated

11 器件和文档支持

11.1 器件支持

11.1.1 Third-Party Products Disclaimer

TI'S PUBLICATION OF INFORMATION REGARDING THIRD-PARTY PRODUCTS OR SERVICES DOES NOT CONSTITUTE AN ENDORSEMENT REGARDING THE SUITABILITY OF SUCH PRODUCTS OR SERVICES OR A WARRANTY, REPRESENTATION OR ENDORSEMENT OF SUCH PRODUCTS OR SERVICES, EITHER ALONE OR IN COMBINATION WITH ANY TI PRODUCT OR SERVICE.

11.2 商标

PowerPAD is a trademark of Texas Instruments.

11.3 静电放电警告



这些装置包含有限的内置 ESD 保护。 存储或装卸时，应将导线一起截短或将装置放置于导电泡棉中，以防止 MOS 门极遭受静电损伤。

11.4 Glossary

SLYZ022 — *TI Glossary*.

This glossary lists and explains terms, acronyms, and definitions.

12 机械、封装和可订购信息

以下页中包括机械、封装和可订购信息。这些信息是针对指定器件可提供的最新数据。这些数据会在无通知且不对本文档进行修订的情况下发生改变。欲获得该数据表的浏览器版本，请查阅左侧的导航栏。

版权 © 2016, Texas Instruments Incorporated

重要声明

德州仪器(TI) 及其下属子公司有权根据 JESD46 最新标准, 对所提供的产品和服务进行更正、修改、增强、改进或其它更改， 并有权根据 JESD48 最新标准中止提供任何产品和服务。客户在下订单前应获取最新的相关信息, 并验证这些信息是否完整且是最新的。所有产品的销售都遵循在订单确认时所提供的TI 销售条款与条件。

TI 保证其所销售的组件的性能符合产品销售时 TI 半导体产品销售条件与条款的适用规范。仅在 TI 保证的范围内，且 TI 认为 有必要时才会使用测试或其它质量控制技术。除非适用法律做出了硬性规定，否则没有必要对每种组件的所有参数进行测试。

TI 对应用帮助或客户产品设计不承担任何义务。客户应对其使用 TI 组件的产品和应用自行负责。为尽量减小与客户产品和应 用相关的风险，客户应提供充分的设计与操作安全措施。

TI 不对任何 TI 专利权、版权、屏蔽作品权或其它与使用了 TI 组件或服务的组合设备、机器或流程相关的 TI 知识产权中授予 的直接或隐含权限作出任何保证或解释。TI 所发布的与第三方产品或服务有关的信息，不能构成从 TI 获得使用这些产品或服 务的许可、授权、或认可。使用此类信息可能需要获得第三方的专利权或其它知识产权方面的许可，或是 TI 的专利权或其它 知识产权方面的许可。

对于 TI 的产品手册或数据表中 TI 信息的重要部分，仅在没有对内容进行任何篡改且带有相关授权、条件、限制和声明的情况 下才允许进行复制。TI 对此类篡改过的文件不承担任何责任或义务。复制第三方的信息可能需要服从额外的限制条件。

在转售 TI 组件或服务时，如果对该组件或服务参数的陈述与 TI 标明的参数相比存在差异或虚假成分，则会失去相关 TI 组件 或服务的所有明示或暗示授权，且这是不正当的、欺诈性商业行为。TI 对任何此类虚假陈述均不承担任何责任或义务。

客户认可并同意，尽管任何应用相关信息或支持仍可能由 TI 提供，但他们将独力负责满足与其产品及在其应用中使用 TI 产品 相关的所有法律、法规和安全相关要求。客户声明并同意，他们具备制定与实施安全措施所需的全部专业技术和知识，可预见 故障的危险后果、监测故障及其后果、降低有可能造成人身伤害的故障的发生机率并采取适当的补救措施。客户将全额赔偿因 在此类安全关键应用中使用任何 TI 组件而对 TI 及其代理造成的任何损失。

在某些场合中，为了推进安全相关应用有可能对 TI 组件进行特别的促销。TI 的目标是利用此类组件帮助客户设计和创立其特 有的可满足适用的功能安全性标准和要求的终端产品解决方案。尽管如此，此类组件仍然服从这些条款。

TI 组件未获得用于 FDA Class III（或类似的生命攸关医疗设备）的授权许可，除非各方授权官员已经达成了专门管控此类使 用的特别协议。

只有那些 TI 特别注明属于军用等级或"增强型塑料"的 TI 组件才是设计或专门用于军事/航空应用或环境的。购买者认可并同 意，对并非指定面向军事或航空航天用途的 TI 组件进行军事或航空航天方面的应用，其风险由客户单独承担，并且由客户独 力负责满足与此类使用相关的所有法律和法规要求。

TI 已明确指定符合 ISO/TS16949 要求的产品，这些产品主要用于汽车。在任何情况下，因使用非指定产品而无法达到 ISO/TS16949 要求，TI不承担任何责任。

	产品		应用
数字音频	www.ti.com.cn/audio	通信与电信	www.ti.com.cn/telecom
放大器和线性器件	www.ti.com.cn/amplifiers	计算机及周边	www.ti.com.cn/computer
数据转换器	www.ti.com.cn/dataconverters	消费电子	www.ti.com/consumer-apps
DLP® 产品	www.dlp.com	能源	www.ti.com/energy
DSP - 数字信号处理器	www.ti.com.cn/dsp	工业应用	www.ti.com.cn/industrial
时钟和计时器	www.ti.com.cn/clockandtimers	医疗电子	www.ti.com.cn/medical
接口	www.ti.com.cn/interface	安防应用	www.ti.com.cn/security
逻辑	www.ti.com.cn/logic	汽车电子	www.ti.com.cn/automotive
电源管理	www.ti.com.cn/power	视频和影像	www.ti.com.cn/video
微控制器 (MCU)	www.ti.com.cn/microcontrollers		
RFID 系统	www.ti.com.cn/rfidsys		
OMAP应用处理器	www.ti.com/omap		
无线连通性	www.ti.com.cn/wirelessconnectivity	德州仪器在线技术支持社区	www.deyisupport.com

邮寄地址： 上海市浦东新区世纪大道1568 号，中建大厦32 楼邮政编码： 200122
Copyright © 2016, 德州仪器半导体技术（上海）有限公司

PACKAGING INFORMATION

Orderable Device	Status (1)	Package Type	Package Drawing	Pins	Package Qty	Eco Plan (2)	Lead/Ball Finish (6)	MSL Peak Temp (3)	Op Temp (°C)	Device Marking (4/5)	Samples
DRV2511QDAPRQ1	ACTIVE	HTSSOP	DAP	32	2000	Green (RoHS & no Sb/Br)	CU NIPDAU	Level-3-260C-168 HR	-40 to 125	DRV2511Q	Samples

(1) The marketing status values are defined as follows:
ACTIVE: Product device recommended for new designs.
LIFEBUY: TI has announced that the device will be discontinued, and a lifetime-buy period is in effect.
NRND: Not recommended for new designs. Device is in production to support existing customers, but TI does not recommend using this part in a new design.
PREVIEW: Device has been announced but is not in production. Samples may or may not be available.
OBSOLETE: TI has discontinued the production of the device.

(2) Eco Plan - The planned eco-friendly classification: Pb-Free (RoHS), Pb-Free (RoHS Exempt), or Green (RoHS & no Sb/Br) - please check http://www.ti.com/productcontent for the latest availability information and additional product content details.
TBD: The Pb-Free/Green conversion plan has not been defined.
Pb-Free (RoHS): TI's terms "Lead-Free" or "Pb-Free" mean semiconductor products that are compatible with the current RoHS requirements for all 6 substances, including the requirement that lead not exceed 0.1% by weight in homogeneous materials. Where designed to be soldered at high temperatures, TI Pb-Free products are suitable for use in specified lead-free processes.
Pb-Free (RoHS Exempt): This component has a RoHS exemption for either 1) lead-based flip-chip solder bumps used between the die and package, or 2) lead-based die adhesive used between the die and leadframe. The component is otherwise considered Pb-Free (RoHS compatible) as defined above.
Green (RoHS & no Sb/Br): TI defines "Green" to mean Pb-Free (RoHS compatible), and free of Bromine (Br) and Antimony (Sb) based flame retardants (Br or Sb do not exceed 0.1% by weight in homogeneous material)

(3) MSL, Peak Temp. - The Moisture Sensitivity Level rating according to the JEDEC industry standard classifications, and peak solder temperature.

(4) There may be additional marking, which relates to the logo, the lot trace code information, or the environmental category on the device.

(5) Multiple Device Markings will be inside parentheses. Only one Device Marking contained in parentheses and separated by a "~" will appear on a device. If a line is indented then it is a continuation of the previous line and the two combined represent the entire Device Marking for that device.


(6) Lead/Ball Finish - Orderable Devices may have multiple material finish options. Finish options are separated by a vertical ruled line. Lead/Ball Finish values may wrap to two lines if the finish value exceeds the maximum column width.

Important Information and Disclaimer: The information provided on this page represents TI's knowledge and belief as of the date that it is provided. TI bases its knowledge and belief on information provided by third parties, and makes no representation or warranty as to the accuracy of such information. Efforts are underway to better integrate information from third parties. TI has taken and continues to take reasonable steps to provide representative and accurate information but may not have conducted destructive testing or chemical analysis on incoming materials and chemicals. TI and TI suppliers consider certain information to be proprietary, and thus CAS numbers and other limited information may not be available for release.


In no event shall TI's liability arising out of such information exceed the total purchase price of the TI part(s) at issue in this document sold by TI to Customer on an annual basis.

TAPE AND REEL INFORMATION

REEL DIMENSIONS




TAPE DIMENSIONS



A0	Dimension designed to accommodate the component width
B0	Dimension designed to accommodate the component length
K0	Dimension designed to accommodate the component thickness
W	Overall width of the carrier tape
P1	Pitch between successive cavity centers


QUADRANT ASSIGNMENTS FOR PIN 1 ORIENTATION IN TAPE



*All dimensions are nominal

Device	Package Type	Package Drawing	Pins	SPQ	Reel Diameter (mm)	Reel Width W1 (mm)	A0 (mm)	B0 (mm)	K0 (mm)	P1 (mm)	W (mm)	Pin1 Quadrant
DRV2511QDAPRQ1	HTSSOP	DAP	32	2000	330.0	24.4	8.6	11.5	1.6	12.0	24.0	Q1


TAPE AND REEL BOX DIMENSIONS



*All dimensions are nominal

Device	Package Type	Package Drawing	Pins	SPQ	Length (mm)	Width (mm)	Height (mm)
DRV2511QDAPRQ1	HTSSOP	DAP	32	2000	350.0	350.0	43.0

DAP (R–PDSO–G32) PowerPAD™ PLASTIC SMALL–OUTLINE PACKAGE



NOTES:
A. All linear dimensions are in millimeters.
B. This drawing is subject to change without notice.
C. Body dimensions do not include mold flash or protrusion. Mold flash and protrusion shall not exceed 0.15 per side.
D. This package is designed to be soldered to a thermal pad on the board. Refer to Technical Brief, PowerPad Thermally Enhanced Package, Texas Instruments Literature No. SLMA002 for information regarding recommended board layout. This document is available at www.ti.com <http://www.ti.com>.
F. Falls within JEDEC MO–153 Variation DCT.

PowerPAD is a trademark of Texas Instruments.


DAP (R–PDSO–G32) PowerPAD™ PLASTIC SMALL OUTLINE

THERMAL INFORMATION

This PowerPAD™ package incorporates an exposed thermal pad that is designed to be attached to a printed circuit board (PCB). The thermal pad must be soldered directly to the PCB. After soldering, the PCB can be used as a heatsink. In addition, through the use of thermal vias, the thermal pad can be attached directly to the appropriate copper plane shown in the electrical schematic for the device, or alternatively, can be attached to a special heatsink structure designed into the PCB. This design optimizes the heat transfer from the integrated circuit (IC).

For additional information on the PowerPAD package and how to take advantage of its heat dissipating abilities, refer to Technical Brief, PowerPAD Thermally Enhanced Package, Texas Instruments Literature No. SLMA002 and Application Brief, PowerPAD Made Easy, Texas Instruments Literature No. SLMA004. Both documents are available at www.ti.com.

The exposed thermal pad dimensions for this package are shown in the following illustration.



Top View

Exposed Thermal Pad Dimensions

4206319–12/M 09/13

NOTE: All linear dimensions are in millimeters

PowerPAD is a trademark of Texas Instruments.

重要声明和免责声明

TI 均以“原样”提供技术性及可靠性数据（包括数据表）、设计资源（包括参考设计）、应用或其他设计建议、网络工具、安全信息和其他资源，不保证其中不含任何瑕疵，且不做任何明示或暗示的担保，包括但不限于对适销性、适合某特定用途或不侵犯任何第三方知识产权的暗示担保。

所述资源可供专业开发人员应用TI 产品进行设计使用。您将对以下行为独自承担全部责任：(1) 针对您的应用选择合适的TI 产品；(2) 设计、验证并测试您的应用；(3) 确保您的应用满足相应标准以及任何其他安全、安保或其他要求。所述资源如有变更，恕不另行通知。TI 对您使用所述资源的授权仅限于开发资源所涉及TI 产品的相关应用。除此之外不得复制或展示所述资源，也不提供其它TI或任何第三方的知识产权授权许可。如因使用所述资源而产生任何索赔、赔偿、成本、损失及债务等，TI对此概不负责，并且您须赔偿由此对TI 及其代表造成的损害。

TI 所提供产品均受TI 的销售条款 (http://www.ti.com.cn/zh-cn/legal/termsofsale.html) 以及ti.com.cn上或随附TI产品提供的其他可适用条款的约束。TI提供所述资源并不扩展或以其他方式更改TI 针对TI 产品所发布的可适用的担保范围或担保免责声明。

邮寄地址：上海市浦东新区世纪大道 1568 号中建大厦 32 楼，邮政编码：200122
Copyright © 2019 德州仪器半导体技术（上海）有限公司