	.35 [8.89]	• •	3.00 [7 2.50 [6 1.00 [29 1	3.50] SMA Connec	
.2	25 [6.35] -	پ 1.00 [25	40]	4X Ø.100[2.54] Mounting Holes 4	Places .062 [1.57]
Electrical:	Specif	1.00 [25.	IS:	Mounting Holes 4	.062 [1.57] 423 Black Oak Ridge Rd. Wayne, NJ 07470
Electrical: Frequency Range:	Speci 5-1000	fication	I S: Mhz	Mounting Holes 4	.062 [1.57] 423 Black Oak Ridge Rd.
Electrical: Frequency Range: Insertion Loss:	Speci 5-1000 1.2	-	IS:	Mounting Holes 4 50 [12.65] SigaTek	.062 [1.57] 423 Black Oak Ridge Rd. Wayne, NJ 07470 Ph: 973-706-8475, Fax: 973-832-4435 www.sigatek.com
Electrical: Frequency Range: nsertion Loss: Amplitude Balance:	Speci 5-1000	fication	Mhz Max	Mounting Holes 4	.062 [1.57] 423 Black Oak Ridge Rd. Wayne, NJ 07470 Ph: 973-706-8475, Fax: 973-832-4435 www.sigatek.com 4-way Power Combiner
Electrical: Frequency Range: nsertion Loss: Amplitude Balance: solation:	Speci 5-1000 1.2 0.3	fication dB dB	Mhz Max Max	Mounting Holes 4 50 [12.65] SP41240S	.062 [1.57] 423 Black Oak Ridge Rd. Wayne, NJ 07470 Ph: 973-706-8475, Fax: 973-832-4435 www.sigatek.com 4-way Power Combiner SMA-Connectors
Electrical: Frequency Range: nsertion Loss: Amplitude Balance: solation: Phase Balance:	Speci 5-1000 1.2 0.3 25	dB dB dB dB	Mhz Max Max Min	Mounting Holes 4 50 [12.65] SigaTek	.062 [1.57] 423 Black Oak Ridge Rd. Wayne, NJ 07470 Ph: 973-706-8475, Fax: 973-832-4435 www.sigatek.com 4-way Power Combiner SMA-Connectors
Electrical: Frequency Range: nsertion Loss: Amplitude Balance: solation: Phase Balance: /SWR Input:	Speci 5-1000 1.2 0.3 25 5	dB dB dB dB	Mhz Max Max Min Max	Mounting Holes 4 50 [12.65] Sparek SP41240S Dimensions are in inches and (mm Decimal Tolerance: 2 place +- 0.020	.062 [1.57] 423 Black Oak Ridge Rd. Wayne, NJ 07470 Ph: 973-706-8475, Fax: 973-832-4435 www.sigatek.com 4-way Power Combiner SMA-Connectors
Electrical: Frequency Range: Insertion Loss: Amplitude Balance: Isolation: Phase Balance: VSWR Input: VSWR Output:	Speci 5-1000 1.2 0.3 25 5 1.40:1	dB dB dB dB Deg. Watt	Mhz Max Max Min Max Max Max	Mounting Holes 4 50 [12.65] Spatek SP41240S Dimensions are in inches and (mm Decimal Tolerance:	.062 [1.57] 423 Black Oak Ridge Rd. Wayne, NJ 07470 Ph: 973-706-8475, Fax: 973-832-4435 www.sigatek.com 4-way Power Combiner SMA-Connectors
Electrical: Frequency Range: Insertion Loss: Amplitude Balance: Isolation: Phase Balance: VSWR Input: VSWR Output: Power at SUM port:	Speci 5-1000 1.2 0.3 25 5 1.40:1 1.40:1	dB dB dB dB Deg.	Mhz Max Max Max Min Max Max Max Max	Mounting Holes 4 50 [12.65] Spate Spate Spate Dimensions are in inches and (mm Decimal Tolerance: 2 place +- 0.020 3 place +- 0.010	.062 [1.57] 423 Black Oak Ridge Rd. Wayne, NJ 07470 Ph: 973-706-8475, Fax: 973-832-4435 www.sigatek.com 4-way Power Combiner SMA-Connectors
Electrical:	Speci 5-1000 1.2 0.3 25 5 1.40:1 1.40:1 1.40:1 25	fication dB dB dB Deg. Watt 85 gr	Mhz Max Max Min Max Max Max Max Max	Mounting Holes 4 50 [12.65] Sparek SP41240S Dimensions are in inches and (mm Decimal Tolerance: 2 place +- 0.020	.062 [1.57] 423 Black Oak Ridge Rd. Wayne, NJ 07470 Ph: 973-706-8475, Fax: 973-832-4435 www.sigatek.com 4-way Power Combiner SMA-Connectors n) CAGE CODE : 69UC1