		.125 [3.18]	2.00	4.00 [101.60] N Connectors 5 Places SUM	
		() () () () () () () () () () () () () (1 2	0.125 [ø3.18] Mounting Holes [95.25] 3 4	3.40 [86.36]
Electrical: Frequency Range:	20-400	ications	Mhz	I SigaTek	423 Black Oak Ridge Rd. Wayne, NJ 07470 Ph: 973-706-8475, Fax: 973-832-4435
Frequency Range: nsertion Loss:	20-400 0.8	ications	Mhz Max	SigaTek	Wayne, NJ 07470 Ph: 973-706-8475, Fax: 973-832-4435 www.sigatek.com
Frequency Range: nsertion Loss: Amplitude Balance: solation:	20-400	ications	Mhz	[25.40] TYP	Wayne, NJ 07470 Ph: 973-706-8475, Fax: 973-832-4435 www.sigatek.com 4-way Power Combiner
Frequency Range: nsertion Loss: Amplitude Balance: solation: Phase Balance:	20-400 0.8 0.5 20 6	dB dB	Mhz Max Max Min Max	SigaTek	Wayne, NJ 07470 Ph: 973-706-8475, Fax: 973-832-4435 www.sigatek.com
Frequency Range: nsertion Loss: Amplitude Balance: solation: Phase Balance: /SWR Input:	20-400 0.8 0.5 20 6 1.30:1	dB dB dB dB	Mhz Max Max Min Max Max	ISIGATEK SP41041N Dimensions are in inches and (mm) Decimal Tolerance:	Wayne, NJ 07470 Ph: 973-706-8475, Fax: 973-832-4435 www.sigatek.com 4-way Power Combiner N-Connectors
Frequency Range: nsertion Loss: Amplitude Balance: solation: Phase Balance: /SWR Input: /SWR Output:	20-400 0.8 0.5 20 6 1.30:1 1.30:1	dB dB dB dB Deg.	Mhz Max Max Min Max Max Max Max	[25.40] SigaTek SP41041N Dimensions are in inches and (mm) Decimal Tolerance: 2 place +- 0.020	Wayne, NJ 07470 Ph: 973-706-8475, Fax: 973-832-4435 www.sigatek.com 4-way Power Combiner
Frequency Range: nsertion Loss: Amplitude Balance: solation: Phase Balance: /SWR Input: /SWR Output: Power at SUM port:	20-400 0.8 0.5 20 6 1.30:1 1.30:1 400	dB dB dB dB Deg. Watt	Mhz Max Min Max Max Max Max Max	ISIGATEK SP41041N Dimensions are in inches and (mm) Decimal Tolerance:	Wayne, NJ 07470 Ph: 973-706-8475, Fax: 973-832-4435 www.sigatek.com 4-way Power Combiner N-Connectors
Frequency Range: nsertion Loss: Amplitude Balance: solation: Phase Balance: /SWR Input: /SWR Output: Power at SUM port: /Veight:	20-400 0.8 0.5 20 6 1.30:1 1.30:1 400 1.21 lb	dB dB dB Deg. Watt 550 gr	Mhz Max Max Min Max Max Max Max	[25.40] SigaTek SP41041N Dimensions are in inches and (mm) Decimal Tolerance: 2 place +- 0.020 3 place +- 0.010	Wayne, NJ 07470 Ph: 973-706-8475, Fax: 973-832-4435 www.sigatek.com 4-way Power Combiner N-Connectors CAGE CODE : 69UC1
Frequency Range: nsertion Loss: Amplitude Balance: solation: Phase Balance: /SWR Input: /SWR Output: Power at SUM port:	20-400 0.8 0.5 20 6 1.30:1 1.30:1 400	dB dB dB Deg. Watt 550 gr	Mhz Max Min Max Max Max Max Max	[25.40] SigaTek SP41041N Dimensions are in inches and (mm) Decimal Tolerance: 2 place +- 0.020	Wayne, NJ 07470 Ph: 973-706-8475, Fax: 973-832-4435 www.sigatek.com 4-way Power Combiner N-Connectors CAGE CODE : 69UC1