



Waveguide Bandpass Filter, F Band, 105 to 140 GHz

Description:

Model SWF-13435330-08-B1 is an F band waveguide bandpass filter with a passband frequency of 105 to 140 GHz and rejection frequencies from DC to 94 GHz and 145 to 180 GHz. The nominal insertion loss of the bandpass filter is 2.5 dB and the typical rejection is 40 dB. Since both low end and high end cut off frequencies can be selected by modifying the design, custom designs are available under different model numbers.



Features:

- Low Cost
- Low Insertion Loss
- High Rejection

Applications:

- IEEE 802.11ad WiGig Systems
- Communication Systems
- Radar Systems
- Sub-assemblies

Electrical Specifications:

Parameter	Minimum	Typical	Maximum
Passband Frequency	105 GHz		140 GHz
Passband Insertion Loss		2.5 dB	
Rejection Frequency, Low Side	DC		94 GHz
Rejection Frequency, High Side	145 GHz		180 GHz
Rejection		40 dB	
Specification Temperature		+25°C	
Operating Temperature	-40°C		+85°C

Mechanical Specifications:


Item	Specification
Waveguide	WR-08 with UG-387/U-M Flange
Size	1.20" (L) X 0.75" (W) X 0.75" (H)
Material	Brass
Finish	Gold Plated
Weight	2.3 Oz
Outline	WF-BF-C






Waveguide Bandpass Filter, F Band, 105 to 140 GHz

Simulated Data



Mechanical Outline: (Unless otherwise specified, all dimensions are in inches)



Note:

- All data presented are simulated. Actual data may vary.
- SAGE Millimeter, Inc. reserves the right to change the information presented without notice.

Caution:

- Any foreign objects in the waveguide will degrade performance and/or damage the device.



www.sagemillimeter.com | 3043 Kashiwa Street, Torrance, CA 90505
 Phone: 424-757-0168 | Fax: 424-757-0188 | Email: sales@sagemillimeter.com