2 Way-0° 75Ω 5 to 1200 MHz

The Big Deal

- High performance at a very low cost
- Very small form size (0.250" x 0.310" x 0.133" high)



Product Overview

The CDP-2-122-75+ is a 2-way power splitter featuring a flat, laser-marked, "Top-Hat" cover for faster pick and place manufacturing throughput. Installed as a single component with a small footprint (0.250" x 0.310") and low height (0.133"), it utilizes square-core, all-welded construction to handle up to 1W RF power. The open-style case is aqueous washable and RoHS compliant.

Feature	Advantages				
Wide bandwidth at a low cost	5-1200 MHz bandwidth accomodates forward & return CATV transmission bands				
Low insertion loss, Excellent return loss	Excellent VSWR (1.01-1.23 in/1.10-1.25 out) for low-loss performance in both directions				
Very good isolation	20-25 dB for consistent performance under changing loads				
Very good amplitude and phase unbalance	0.2 dB typ. amplitude unbalance and 3.0° typ. phase unbalance help reduce unwanted noise and harmonics				

Notes

A. Performance and quality attributes and conditions not expressly stated in this specification document are intended to be excluded and do not form a part of this specification document.

B. Electrical specifications and performance data contained in this specification document are based on Mini-Circuit's applicable established test performance criteria and measurement instructions.

C. The parts covered by this specification document are subject to Mini-Circuit standard limited warranty and terms and conditions (collectively, "Standard Terms"); Purchasers of this part are entitled to the rights and benefits contained therein. For a full statement of the Standard Terms and the exclusive rights and remedies thereunder, please visit Mini-Circuits website at www.minicircuits.com/MCLStore/terms.jsp

CDP-2-122-75+

2 Way-0°

Maximum Ratings

Operating Temperature

Power Input (as a splitter)

Storage Temperature

Internal Dissipation

75Ω

-40°C to 85°C

-55°C to 100°C

0.125W max.

1W max.

5 to 1200 MHz

Features

- wideband, 5 to 1200 MHz
- low insertion loss, 0.8 dB typ.
- excellent matching return loss, 20 dB typ.
- · aqueous washable

Applications

CASE STYLE: TT1491-2

+RoHS Compliant

The +Suffix identifies RoHS Compliance. See our web site for RoHS Compliance methodologies and qualifications


	Available Tape and Reel at no extra cost
Reel Size	Devices/Reel
7"	20, 50, 100, 200
13"	500, 1000

Pin Connections

SUM PORT	6
PORT 1	3
PORT 2	4
GROUND	1
NOT USED	2,5
EXT. RESISTOR 165Ω	3,4

Permanent damage may occur if any of these limits are exceeded


Outline Drawing



Outline Dimensions (inch)

wt	K	J	Н	G	F	Е	D	С	В	Α
grams	.059	.328	.112	.044	.055	.050	.100	.133	.310	.250
0.35	1.50	8.33	2.84	1.12	1.40	1.27	2.54	3.38	7.87	6.35

Demo Board MCL P/N: TB-698+



- NOTES: 1. TRACE WIDTH IS SHOWN FOR ROGERS RO4350B WITH DIELECTRIC THICKNESS 0.030" ± 0.002"; COPPER: 1/2 0.7. EACH SIDE. FOR OTHER MATERIALS TRACE WIDTH MAY NEED TO BE MODIFIED. 2. CHIP COMPONENT FOOT PRINT SHOWN FOR REFERENCE. FOR COMPONENT VALUES REFER TO TB—508+.
 3. BOTTOM SIDE OF THE POB IS CONTINUOUS GROUND PLANE. DENOTES POE COPPER LAYOUT WITH SMOBC (SOLDER MASK OVER BARE COPPER).

 - DENOTES COPPER LAND PATTERN FREE OF SOLDER MASK.


• cellular VHF/UHF

- DOCSIS® 3.1 Systems
- · communication systems

Electrical Specifications at 25°C

Parameter	Frequency (MHz)	Min.	Тур.	Max.	Unit		
Frequency Range		5		1200	MHz		
	5-50	_	0.4	0.8			
Insertion Loss Above 3.0 dB	50-600	_	0.6	1.0	dB		
	600-1200	_	1.0	1.8			
	5-50	20	24	_			
Isolation	50-600	20	25	_	-ID		
Isolation	600-1000	17	20	_	dB		
	1000-1200	15	18	_			
	5-50	_	1.0	3.0			
Phase Unbalance	50-600	_	1.0	3.0	Degree		
	600-1200	_	2.0	5.0			
	5-50	_	0.2	0.5			
Amplitude Unbalance	50-600	_	0.2	0.4	dB		
	600-1200	_	0.2	0.6			
	5-50	_	1.05	1.2			
VSWR (Port S)	50-600	_	1.10	1.2	:1		
	600-1200	_	1.25	1.3			
	5-50	_	1.20	1.5			
VSWR (Port 1-2)	50-600	_	1.15	1.3	:1		
	600-1200	_	1.10	1.45			

Electrical Schematic



- A. Performance and quality attributes and conditions not expressly stated in this specification document are intended to be excluded and do not form a part of this specification document.


 B. Electrical specifications and performance data contained in this specification document are based on Mini-Circuit's applicable established test performance criteria and measurement instructions.


 C. The parts covered by this specification document are subject to Mini-Circuits standard limited warranty and terms and conditions (collectively, "Standard Terms"); Purchasers of this part are entitled to the rights and benefits contained therein. For a full statement of the Standard Terms and the exclusive rights and remedies thereunder, please visit Mini-Circuits' website at www.minicircuits.com/MCLStore/terms.jsp


Typical Performance Data

Frequency (MHz)	Total Loss¹ (dB)		Amplitude Unbalance (dB)	Isolation (dB)	Phase Unbalance (deg.)	VSWR S	VSWR 1	VSWR 2
	S-1 S-2	S-2						
5.00	3.41	3.16	0.25	25.89	0.86	1.05	1.24	1.17
10.00	3.36	3.14	0.22	29.14	0.49	1.03	1.18	1.12
50.00	3.36	3.17	0.19	31.82	0.01	1.02	1.13	1.09
100.00	3.39	3.19	0.20	30.64	0.14	1.02	1.13	1.09
200.00	3.45	3.24	0.21	29.20	0.27	1.03	1.11	1.09
400.00	3.55	3.34	0.21	27.35	0.40	1.06	1.07	1.10
600.00	3.68	3.47	0.22	25.55	0.41	1.07	1.04	1.12
700.00	3.75	3.53	0.22	24.90	0.35	1.07	1.06	1.13
800.00	3.83	3.61	0.22	24.31	0.26	1.07	1.10	1.15
900.00	3.93	3.71	0.22	23.80	0.08	1.06	1.14	1.16
1050.00	4.11	3.87	0.24	23.46	0.30	1.06	1.21	1.20
1200.00	4.34	4.06	0.27	23.56	0.84	1.09	1.28	1.23

^{1.} Total Loss = Insertion Loss + 3dB splitter loss.







Notes
A. Performance and quality attributes and conditions not expressly stated in this specification document are intended to be excluded and do not form a part of this specification document.
B. Electrical specifications and performance data contained in this specification document are based on Mini-Circuit's applicable established test performance criteria and measurement instructions.
C. The parts covered by this specification document are subject to Mini-Circuits standard limited warranty and terms and conditions (collectively, "Standard Terms"); Purchasers of this part are entitled to the rights and benefits contained therein. For a full statement of the Standard Terms and the exclusive rights and remedies thereunder, please visit Mini-Circuits' website at www.minicircuits.com/MCLStore/terms.jsp