RF Transformer

 50Ω

0.03 to 20 MHz

CASE STYLE: W38

T36-1+

+RoHS Compliant The +Suffix identifies RoHS Compliance. See our web site for RoHS Compliance methodologies and qualifications

Maximum Ratings

Operating Temperature	-20°C to 85°C
Storage Temperature	-55°C to 100°C
RF Power	0.25W
DC Current	30mA
Dormonant damage may easy if any	of those limits are evenedo

Pin Connections

PRIMARY DOT	4
PRIMARY	6
SECONDARY DOT	3
SECONDARY	1
SECONDARY CT	
NOT USED	2,5

Features

- good return loss
- also available with plug-in (X65) surface mount gull-wing (KK81) leads

Applications

- · amateur radio
- · impedance matching

Transformer Electrical Specifications

Ω RATIO (Secondary/Primary)	FREQUENCY (MHz)	INSERTION LOSS*		
		3 dB MHz	2 dB MHz	1 dB MHz
36	0.03-20	0.03-20	0.05-10	0.1-5

Typical Performance Data

INSERTION

LOSS

(dB)

2.44

1.60

0.89

0.69

0.67

0.38

0.50

FREQUENCY

(MHz)

0.03

0.05

0.05

0.10

0.20

0.27

0.47


2 17

4.66

10

20.00

Outline Drawing




E	D	С	В	Α
.042	.010	.23	.27	.30
1.07	0.25	5.84	6.86	7.62
- 1	K	J	н	G
_	1.	U		0
.036	.31	.09	.05	.100
			.23 .010 .042 5.84 0.25 1.07	.27 .23 .010 .042 6.86 5.84 0.25 1.07

Outline Dimensions (inch)

F	E	D	С	В	Α
.020	.042	.010	.23	.27	.30
0.51	1.07	0.25	5.84	6.86	7.62
wt	L	K	J	Н	G
grams	.036	.31	.09	.05	.100
0.50	0.91	7.87	2.29	1 27	2.54

	T36-1 INSERTION LOSS				
С	(a) 4.0 -				
•	NSERTION LOSS 1.0 -	\			/
SEC	OERTIC -			/	
	S 1.0 -				

0.01



INPUT

R. LOSS

(dB)

6.98

9.75

15.22 19.88

20.32

24.87

16.92

10.04

Config.

- A. Performance and quality attributes and conditions not expressly stated in this specification document are intended to be excluded and do not form a part of this specification document.

 B. Electrical specifications and performance data contained in this specification document are based on Mini-Circuit's applicable established test performance criteria and measurement ins.

 C. The parts covered by this specification document are subject to Mini-Circuits standard limited warranty and terms and conditions (collectively: "Standard Terms"): Purchases of this part. Electrical specifications and performance data contained in this specification document are based on Mini-Circuit's applicable established test performance criteria and measurement instructions.

 The parts covered by this specification document are subject to Mini-Circuits standard limited warranty and terms and conditions (collectively, "Standard Terms"); Purchasers of this part are entitled to the rights and benefits contained therein. For a full statement of the Standard Terms and the exclusive rights and remedies thereunder, please visit Mini-Circuits' website at www.minicircuits.com/MCLStore/terms.jsp

FREQUENCY (MHz)

^{*}Insertion Loss is referenced to mid-band loss, 0.4 dB typ.