RF Transformer

-20°C to 85°C

-55°C to 100°C

0.25W

30mA

 50Ω

DC Current

2 to 200 MHz

Features

- suitable for tin/lead and RoHS solder systems
- good return loss
- excellent amplitude unbalance, 0.1 dB typ. and phase unbalance, 1 deg. typ. in 1 dB band width
- aqueous washable

Applications

• impedance matching

TC9-1G2+

CASE STYLE: AT224-3

+RoHS Compliant The +Suffix identifies RoHS Compliance. See our web site for RoHS Compliance methodologies and qualifications



Pin Connections

Maximum Ratings


Operating Temperature

Storage Temperature


PRIMARY DOT	6
PRIMARY	4
SECONDARY DOT	1
SECONDARY	3
SECONDARY CT	2

Permanent damage may occur if any of these limits are exceeded.

Outline Drawing AT224-3



PCB Land Pattern




Suggested Layout, Tolerance to be within ±002

Outline Dimensions (inch)

F	Е	D	С	В	Α
.025	.030	.050	.150	.150	.150
0.64	0.76	1.27	3.81	3.81	3.81
wt		K	J	Н	G
grams		.030	.190	.065	.028
0.10		0.76	4.83	1.65	0.71

Config. A




Transformer Electrical Specifications


Ω RATIO (Secondary/Primary)	FREQUENCY (MHz)	INSERTION LOSS* 3 dB 2 dB 1 dB		
		MHz	MHz	MHz
9	2-200	2-200	3-100	5-40

^{*} Insertion Loss is referenced to mid-band loss, 0.7 dB typ.

Typical Performance Data

FREQUENCY (MHz)	INSERTION LOSS (dB)	INPUT R. LOSS (dB)	
2.00 3.00 5.00 20.00 29.00 40.00 60.00 80.00 100.00 200.00	1.14 0.98 0.85 0.76 0.80 0.83 0.90 0.99 1.05	9.85 11.35 13.33 15.80 15.77 14.99 13.22 11.5 10.34 6.08	





- A. Performance and quality attributes and conditions not expressly stated in this specification document are intended to be excluded and do not form a part of this specification document.

 B. Electrical specifications and performance data contained in this specification document are based on Mini-Circuit's applicable established test performance criteria and measurement instructions.

 C. The parts covered by this specification document are subject to Mini-Circuits standard limited warranty and terms and conditions (collectively, "Standard Terms"); Purchasers of this part are entitled to the rights and benefits contained therein. For a full statement of the Standard Terms and the exclusive rights and remedies thereunder, please visit Mini-Circuits' website at www.minicircuits.com/MCLStore/terms.jsp