

# **DIRECTIONAL COUPLER**

C10-0450

The C10-0450 is a broadband 4-50 GHz, 10 dB directional coupler. The multisection tri-plate stripline design exhibits excellent coupling flatness and VSWR to 50 GHz. Custom designs are also available, contact the factory for details.



#### **Features**


- Broadband Performance
- Excellent Coupling Flatness
- High Directivity
- Low VSWR
- Microwave Power Dividers & Couplers App Note

### **Electrical Specifications**

Parameter <sup>1</sup>	Frequency Range (GHz)	Min	Тур	Max
Mean Coupling (dB)	4-50		10	
Amplitude Flatness (dB) <sup>2</sup>	4-50		±0.5	±1.5
Direct Line Insertion Loss (dB)	4-50			2.5
VSWR	4-40		1.35	1.55
	40-50		1.55	
Directivity (dB)	4-50	9	15	
Weight (g)			35	

<sup>&</sup>lt;sup>1</sup>Specifications guaranteed when operated in a  $50\Omega$  system.

<sup>&</sup>lt;sup>2</sup>Deviation from average coupling.



215 Vineyard Court, Morgan Hill, CA 95037 | Ph: 408.778.4200 | Fax 408.778.4300 | info@markimicrowave.com



# **DIRECTIONAL COUPLER**

C10-0450

Page 2

### **Typical Performance**




Fig. 1. Direct line insertion loss.




Fig. 3. Coupled port power.




Fig. 2. Typical port return loss.




Fig. 4. Typical directivity.

Model Number	Description	
C10-0450	4-50 GHz 10 dB Directional Coupler with 2.40 mm connectors <sup>1</sup>	

<sup>1</sup>Default is 2.4 mm female connectors. Consult factory for other connector options.

Marki Microwave reserves the right to make changes to the product(s) or information contained herein without notice. Marki Microwave makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does Marki Microwave assume any liability whatsoever arising out of the use of or application of any product.

© Marki Microwave, Inc.

