

SPECIFICATION SHEET**JFW MODEL 50PD-134****3 WAY RESISTIVE POWER DIVIDER**

JFW Industries, Inc.
Phone: 317-887-1340
sales@jfwindustries.com
www.jfwindustries.com

Frequency Range	DC-2000 MHz
Impedance	50 Ohms nominal
VSWR	1.2:1 maximum to 500 MHz 1.3:1 maximum to 1000 MHz 1.4:1 maximum to 2000 MHz
Insertion Loss	9.5 dB $\pm$ 0.5 dB
Amplitude Tracking	$\pm$ 0.4 dB
RF Input Power	2 Watts average @ 25°C 100 Watts peak (1 microsecond)
Operating Temperature Range	-40°C to +85°C
RF Connector	N, TNC, or BNC (male or female)
Physical Size	See outline drawings: 092-2328-03 (50PD-134 N) 092-6646-03 (50PD-134 BNC) 092-7002-03 (50PD-134 TNC)

ECR/ECN #	DATE	REV	APPR / DATE	ECR/ECN #	DATE	REV	APPR / DATE
866	10/28/1997	A		18885	07/15/2010	D	TRS 07/15/2010
961	02/05/1998	B		19960	04/07/2011	E	TRS 04/07/2011
9999	11/17/2002	C	SL 11/27/2002	20281	06/29/2011	F	TRS 06/29/2011