

SPECIFICATION SHEET**JFW MODEL 50PD-135****4 WAY RESISTIVE POWER DIVIDER**

JFW Industries, Inc.
Phone: 317-887-1340
sales@jfwindustries.com
www.jfwindustries.com

Frequency Range	DC-2000 MHz
Impedance	50 Ohms nominal
VSWR	1.2:1 maximum DC-500 MHz 1.3:1 maximum 500-1000 MHz 1.4:1 maximum 1000-2000 MHz
Insertion Loss	12 dB $\pm$ 0.5 dB
Amplitude Tracking	$\pm$ 0.4 dB
RF Input Power	2 Watts average @ 25°C 100 Watts peak (1 microsecond)
Operating Temperature Range	-40°C to +85°C
RF Connector	N or BNC female
Physical Size	See outline drawing 092-2328-04 (N) 092-6646-04 (BNC)

ECR/ECN #	DATE	REV	APPR / DATE	ECR/ECN #	DATE	REV	APPR / DATE
	06/15/1995			9999	11/16/2002	C	SL 11/27/2002
873	11/03/1997	A		18885	07/15/2010	D	TRS 07/15/2010
2434	07/20/2000	B					