

SPECIFICATION SHEET**JFW MODEL 75BT-007****BIAS TAP**

JFW Industries, Inc.
Phone: 317-887-1340
sales@jfwindustries.com
www.jfwindustries.com

Frequency Range	100-1750 MHz
Impedance	75 Ohms nominal
VSWR	1.4:1 maximum 100-300 MHz 1.3:1 maximum 300-1750 MHz
Insertion Loss	1.25 dB maximum
DC Breakdown Voltage	200 Volts
DC Current Handling	2 Amps
RF Input Power	2 Watts average
RF Connector	BNC or F (male or female)
DC Connector	Solder Terminal (.040")
Operating Temperature Range	-55°C to +85°C
Physical Size	See outline drawings: 092-2712 (F female to F female) 092-5541 (F male to F female)

ECR/ECN #	DATE	REV	APPR / DATE	ECR/ECN #	DATE	REV	APPR / DATE
	01/13/1998			3078	08/09/2002	C	
1176	10/27/1998	A		9999	09/16/2002	D	SL 09/16/2002
1182	11/05/1998	B		20728	10/05/2011	E	TRS 10/05/2011