SWG-12040-FB

Rev. 1.0

WR-12 Straight Waveguide Section, 4”

Description:



SWG-12040-FB is a 4” long, E-band straight waveguide section with a WR-12 waveguide and UG-387/U circular flanges. The straight waveguide is manufactured with a precision machining process to ensure high quality and ruggedness. The waveguide is offered to cover the frequency range of 60 to 90 GHz.

Features:

- Frequency Range: 60 to 90 GHz
- Rugged Waveguide Configuration
- Low Insertion Loss

Applications:

- Test Instrumentation
- Subassemblies

Mechanical Specifications:

Item	Specification
Waveguide Size	WR-12 Waveguide with UG-387/U Flange
Insertion Length	4.0”
Flange Material	Brass
Waveguide Material	Copper
Finish	Gold Plated
Weight	0.9 Oz
Outline	WG-FE-L

Mechanical Outline: (Unless otherwise specified, all dimensions are in inches [millimeters])



Note:

- SAGE Millimeter, Inc. reserves the right to change the information presented without notice.

www.sagemillimeter.com | 3043 Kashiwa Street, Torrance, CA 90505
Phone: 424-757-0168 | Fax: 424-757-0188 | Email: sales@sagemillimeter.com

Copyright © 2016 by SAGE Millimeter, Inc.

SAGE Millimeter, Inc.