DESCRIPTION

- 76.8 MHz SAW bandpass filter with 40 MHz bandwidth.
- 13.3 x 6.5 mm LCC package.
- RoHS compliant.

TYPICAL PERFORMANCE



Center = 76.8 MHz, 15 MHz/div (187.5 kHz incr)

S11 (1.8-151.8 MHz)



S22 (1.8-151.8 MHz)



Spectrum Microwave
400 Nickerson Road, Marlborough, MA 01752, USA • Phone 1-508-251-6400 • Fax 1-508-251-6401
www.SpectrumMicrowave.com

SPECIFICATION

Parameter	Min	Typ	Max	Units
Center Frequency, F_C [1]	-	76.8	-	MHz
Insertion Loss	-	21.4	22	dB
1.5 dB Bandwidth	40	42.1	-	MHz
3 dB Bandwidth	42	43.6	-	MHz
40 dB Bandwidth	-	50.4	53	MHz
Amplitude Ripple [2]	-	0.85	1	dB p-p
Group Delay Variation [2]	-	28	50	ns p-p
Absolute Delay	-	0.95	-	us
Rejection (10 to 50.3 MHz) [3]	40	44	-	dB
Rejection (103.3 to 150 MHz) [3]	40	48	-	dB
Source and Load Impedance		50		ohms
Temperature Coefficient of Frequency		-86		ppm/˚C
Ambient Temperature	-	25	-	˚C

Notes:
1. Reference frequency. Computed as mean of the 3 dB frequencies.
2. Defined over Fc +/- 19.25 MHz.
3. Dependent upon PC board layout.

MAXIMUM RATINGS

Parameter	Min	Max	Units
Storage Temperature Range	-25	70	˚C
Operating temperature Range	15	35	˚C
Input Power Level	-	13	dBm

MATCHING CIRCUIT



Typical Component values: Ls1 = 180 nH Ls2 = 248 nH
Cp1 = 33 pF Cp2 = 5 pF

Notes:
- Recommend 2% or better tolerance matching components. Typical inductor Q=40.
- Optimum values may change depending on board layout. Values shown are intended as a guide only.

PACKAGE OUTLINE



SUGGESTED FOOTPRINT



Units: mm

Tolerances are ±0.15 mm except where indicated.

Pad Configuration:

Input:	11
Output:	5
Ground:	All other pads

Package Material:
Body: Al_2O_3 ceramic
Lid: *Kovar, Ni* plated
Terminations: *Au* plating 1 µm min, over a 1.3-8.9 µm *Ni* plating

MARKING



ISO 9001 Registered

Spectrum Microwave
400 Nickerson Road, Marlborough, MA 01752, USA • Phone 1-508-251-6400 • Fax 1-508-251-6401
www.SpectrumMicrowave.com