# KR Electronics, Inc.

### **General Description**

KR 2760 is a 65 MHz surface mount bandpass filter. Other center frequencies and bandwidths available. Please consult the factory.

#### Features

- 65 MHz Center Frequency
- 1 dB Bandwidth, 10 MHz min
- Surface Mount Package
- 50  $\Omega$  Source and Load

## **Typical Performance**



## Passband Amplitude & Group Delay

(1 dB/div and 5 nsec/div)

#### Overall Response (10 dB/div)



KR Electronics, Inc. 91 Avenel Street Avenel, NJ 07001	Web Email Phone Fax	www.krfilters.com sales@krfilters.com (732) 636-1900 (732) 636-1982
--	------------------------------	--

© 2007, KR Electronics, Inc.

## **KR Electronics 2760 Bandpass**

## **Specifications**

Parameter	Specification	Typical
Filter type	Bandpass	
Center Frequency	65 MHz	
Insertion Loss	< 2 dB	1 dB
1 dB Bandwidth	10 MHz min	15 MHz
Attenuation at 45 MHz	> 40 dB	
Attenuation at 85 MHz	> 40 dB	
Source and Load	50 Ω	

## **Physical Dimensions**





#### Notes:

- 1. Surface mount package Metal cover (can also be supplied in an package with SMA Connectors)
- 2. Dimensions in inches
- 3. Maximum reflow temperature is 209° C for 15 sec maximum.
- 4. If boards are cleaned after installation, dry units completely.

KR Electronics, Inc. 91 Avenel Street Avenel, NJ 07001	Web Email Phone Fax	www.krfilters.com sales@krfilters.com (732) 636-1900 (732) 636-1982

© 2007, KR Electronics, Inc.